

BT-1001

Uninterruptible Power Supply System

1000VA

Forza's BT series is designed to provide comprehensive electric protection for your personal computer and peripherals.



The small footprint of this UPS makes it ideal for small workspaces at the office or at home. Although compact in size, it provides maximum protection against the constant threat of electric supply interruptions and faults.

Highligts

- Uninterruptible power system with line-interactive topology
- Power protection for home, office and POS equipment
- Automatic voltage regulator (AVR) provides clean and continuous power to connected loads
- Boost and buck AVR for voltage stabilization
- Cold start functionality using battery power
- Six (6) outlets with battery backup, surge and AVR protection
- Two (2) outlets with surge protection only
- Three-year warranty













| MPN | BT-1001 |
|---|---|
| General | |
| Capacity | 1000VA |
| Input | |
| Nominal voltage | 120V |
| Frequency | 50/60Hz (autosensing) |
| AC plug style | 1 NEMA 5-15P |
| Output | |
| Nominal voltage | 120V +/- 10% |
| Frequency | 50/60Hz (60Hz default) |
| Frequency stability | +/- 1Hz battery mode |
| Waveform | Modified sine wave |
| Total outlets | 8 (NEMA 5-15R) |
| Full battery / Surge protection outlets | 6 |
| Surge protection only outlet | 2 |
| Battery | |
| Battery type and quantity | 12V / 9Ah (1) |
| Backup time | 20min* |
| Recharge time | 6~8 hours to 90% after complete discharge |
| Voltage regulation | 0-6 flours to 90 // arter complete discharge |
| High cutoff | 145VAC +/- 5% |
| Boost | 108-111V +/- 5% |
| Buck | 129-132V+/-5% |
| Low cutoff | 89VAC+/- 5% |
| | 89VAC+7-3% |
| Frequency regulation | la di da |
| Automatic frequency selection | Included |
| Line/battery transfer | |
| Transfer time | Typical 2-6ms, 10ms max |
| Low line transfer to battery | 78VAC +/- 5% |
| High line transfer to battery | 145VAC +/- 5% |
| Alarms/Indicators | |
| Visual indicators | AC mode: solid blue |
| | Battery mode: flashes blue every 10 seconds |
| | Fault mode: solid blue |
| Audible | Battery mode: sounds every 10 seconds |
| | Low battery: sounds every second |
| | Overload: sounds every 0.5 second |
| | Fault: continuous sound |
| Protection | |
| Full protection | Line mode: 110%+20%/-10%; shutdown after 5 minutes and go to fault mode |
| | 120%+20%/-10%; shutdown immediately and go to fault mode. |
| | Battery mode:120%+20%/-10%; shutdown immediately |
| Joules | 127J |
| Special features | |
| "Cold start" option | Included |
| Auto charge | Included |
| Environment | |
| Operating temperature | 32-104° F |
| Storage temperature | -4-122° F |
| Relative humidity | 0-90% non-condensing |
| Audible noise | <40dB max |

| MPN | BT-1001 |
|------------------------|-----------------------------|
| Physical appearance | |
| Power switch | Push button |
| Housing | Fire-retardant HIPS plastic |
| Color | Black |
| Cord length | 3.3ft |
| Dimensions | 10.9x4x5.6in |
| Weight | 9.7lb |
| Additional information | |
| Warranty | Three years** |

* Calculated with a single PC plus monitor ** Limited to 2 years on batteries







