forza POWER TECHNOLOGIES

forzaups.com

NT-2402PRO-C

Forza's NT series is designed to provide electric protection for your personal computer and peripherals.



Protect your most delicate and critical electronics with Forza's NT series of smart interactive UPS, designed to keep them unharmed and running smoothly thanks to its many built-in safeguards. From sensitive computers to audio systems or small servers, it offers reliable power backup and surge protection to handle unexpected outages, as well as real-time control over the power supply and a compact, durable housing, making this UPS your ultimate power solution.

Highlights

- Uninterruptible power system (UPS) with built-in protection for a wide range of home and office equipment, from sensitive computers and accessories to audio systems
- Boost and buck Automatic Voltage Regulator (AVR) to monitor and stabilize voltage levels
- USB communication port and advanced ForzaTracker software for intelligent monitoring and management of your UPS and all connected loads in real time
- Six (6) power outlets, four (4) of them with full battery backup and AVR protection
- Network, phone, fax & modem surge protection (RJ-45/11)
- Overload, overcharge, discharge and short circuit protection
- Fire retardant plastic housing
- 4-level load/battery LED indicators, as well as UPS status and fault indicators
- Three-year warranty

Applications

Computers & accessories
Graphic design workstations
Monitors
Personal electronics
Telephones
Modems
Routers
Home audio and video systems

75 minutes backup time**

6 protected outlets

forza Tracker Monitoring software

Ideal for

Computers & accessories

Graphic workstation

Small servers

2400VA

PROTECTION LEVEL 5

+ Breaker
+ Surge Protector
+ Voltage Protector
+ Voltage Regulator
+ Power Back up

MPN		NT-2402PRO-C
Capacity		2400VA/1200W
Input	Nominal voltage	220VAC
	Voltage range	162-268VAC
	Frequency	45-65Hz (autosensing)
	AC plug style	C14
	Included cable	C13 to CEI 23-50
Output	Nominal voltage	220V +/- 10%
	Frequency	50/60Hz
	Frequency stability	+/- 1Hz battery mode
	Waveform	Modified sine wave
	Total outlets	6 (4 x CEI 23-50 and 2 x C13)
	Full battery & surge protection outlets	4
	Surge protection outlets only	2
	Network protection	RJ-45
	Phone/modem/fax protection	RJ-11
	USB management	Included with ForzaTracker software
Battery	Battery type & quantity	Lead-acid battery, 2 pcs
	Battery capacity in V/Ah	12V/9Ah (2)
	Backup time	75 min**
	Recharge time	6 hours to 90% after complete discharge
Voltage regulation	High cutoff	268VAC +/-5%
	Boost 1	198VAC +/-5%
	Buck	242VAC +/-5%
	Low cutoff	162VAC +/-5%
Frequency regulation	Automatic frequency selection	Included
Line/ Battery transfer	Typical transfer time	2-4ms
	Low line transfer to battery	162VAC +/-5%
	High line transfer to battery	268VAC +/-5%
Alarms/ Indicators ***	Visual indicators	AC mode: LED1 (solid green) LED2 (solid green): >0% load level LED3 (solid green): >25% load level LED4 (solid green): >50% load level LED5 (solid green): > 75% load level

EMERGENCY BACKUP POWER SUPPLY · POWER SURGE & SPIKE PROTECTION · AVR PROTECTION · RJ-45 / RJ-11 jack · NOM · ISO 9001 ISO14001 CERTIFIED · FIRE RETARDANT CONSTRUCTION · COLD START FUNCTION · AUDIBLE ALARM

Forza Power Technologies™ is a registered trademark. Other company and product names mentioned herein are trademarks of their respective owners. Mention of third-party products is for informational purposes only and constitutes neither an endorsement nor a recommendation. Forza Power Technologies™ assumes no responsibility with regards to the performance or use of these products. Made in China.

MPN		NT-2402PRO-C
		Battery mode: LED1 (flashing green) LED5 (solid green): battery voltage > 25V LED4 (solid green): battery voltage > 23V LED3 (solid green): battery voltage > 22V LED2 (solid green): battery voltage > 21V LED1 (flashing every second): Low battery Fault mode: LED6 (solid red) LED1 (solid green): overload line mode LED1 (off): overload battery mode LED1 (flashing every 2 seconds): battery replacement
	Audible alarm	Battery mode: sounds every 10 seconds Low battery: sounds every second Overload: sounds every 0.5 second
Protection	Full protection	Overload, overcharge, short circuit, high battery output protection
	Joules	1000J
Special features	"Cold Start" option | Auto charge	
Environment	Operating temperature	32-104°F
	Storage temperature	5-113°F
	Relative humidity	0-95% non-condensing
	Audible noise	<40dB at one meter
Physical appearance	Switch	Illuminated
	Color	Black
	Housing material	Fire retardant plastic
	Product dimensions	15.6 x 5.7 x 8.1 in
	Product weight	24.5 lb.
Additional information	Warranty	3 years*
	Included	UPS unit, USB cable, user manual
	Box dimensions	19.5 x 9.3 x 11.7 in
	Gross weight	26.7 lb.

*2 years on batteries
**Calculated with a single PC plus monitor
*** Check the user manual for detailed explanations on visual and sound indicators functioning

EMERGENCY BACKUP POWER SUPPLY
POWER SURGE & SPIKE PROTECTION
AVR PROTECTION
RJ-45 / RJ-11 jack
NOM
ISO 9001
ISO14001
CERTIFIED
FIRE RETARDANT CONSTRUCTION
COLD START FUNCTION
AUDIBLE ALARM

Forza Power Technologies™ is a registered trademark. Other company and product names mentioned herein are trademarks of their respective owners. Mention of third-party products is for informational purposes only and constitutes neither an endorsement nor a recommendation. Forza Power Technologies™ assumes no responsibility with regards to the performance or use of these products. Made in China.